

GenRad 1863 & 1864 Megohmmeter

p. 1

High Resistance Megohmmeter

IET Labs offers a choice of GenRad megohmmeters to fit many high-resistance measurement needs. Although these two instruments are similar in appearance and accuracy, their operating ranges differ to match differing needs in the laboratory and production area.

FEATURES:

- Easy To Use
- Portable Carrying Case
- Charge Current up to 5mA
- 200 Test Voltages: 10 VDC to 1090 VDC
- 50 k Ω to 200 T Ω (2 x 10¹⁴)
- Analog Output
- 3% Basic Accuracy
- Simple Operation
- Direct Reading, Safe, Stable

**USES:**

- Insulation Resistance on Wire and Cable
- Insulation Resistance on Capacitors
- A Wide Variety of Electronic Components and Devices

Description

The 1863 Megohmmeter is the choice for production and inspection tests. The 1863 will measure resistance at any of five common test voltages up to 500VDC, has fewer controls, and is the lower priced model. It is the best selection for those applications requiring a lesser voltage and resistance range.

The 1864 Megohmmeter is the choice for more demanding applications. It is the more flexible of the two instruments. The test voltage can be set to any value from 10 VDC to 109 VDC in one-volt steps and to 1090 VDC in 10 volt steps. Thus the 1864 can be set to any common, or uncommon test voltage for ceramic, mica or paper capacitors, or other devices. The reverse resistance of rectifiers can be readily measured; the low test voltages are especially useful in measuring solid state diodes. An additional range permits measurements up to 200 T Ω (2 x 10¹⁴ Ω)

Both instruments are easy to use with direct-reading meter indication and lighted range switch that shows the multiplier for each range and voltage. The maximum current possible at the terminals is limited to a 5mA and a panel light near the terminals warns when voltage is present.

Stable power supplies and feedback voltmeter circuit minimize drift and time wasting adjustments. Guard and ground terminals permit measurement of grounded or ungrounded two- or three-terminal resistors. The instruments are supplied in a convenient, portable, Flip-Tilt case that is a stand for the meter in use and protects it in transit and storage.



1863/1864 Megohmmeter

p. 2 of 2

SPECIFICATIONS

1863 and 1864 Megohmmeters

Resistance Accuracy:

1863:(min reading 0.5) Range 1-5: ± 2 (meter reading +1)%
Range 6: $\pm 2\%$ to accuracy above
Range 7: $\pm 4\%$ to accuracy above

1864:(min reading 0.5) Range 1-5: ± 2 (meter reading +1)%
Range 6: $\pm 2\%$ to accuracy above
Range 7: $\pm 3\%$ to accuracy above
Range 8: $\pm 5\%$ to accuracy above

Voltage Accuracy: (across unknown): $\pm 2\%$

Short-Circuit Current:

5mA approximately

Input Terminals:

Front Panel Mounted:
4 Binding Posts
(+) unknown (red)
(-) unknown (red)
guard (red)
ground (silver)

Display:

Analog meter
Caution High Voltage warning indicator

Dimensions:

Flip Tilt Case
(w x h x d) : (9.63 x 10 x 6.75 inches)
(245 x 254 x 172 mm)

Weight:

Approx. 4.4 kg (9.5 lbs) - Net
Approx. 7.0 kg (14 lbs) - Shipping

Power:

100 to 125V or 200 to 250V,
50-400Hz, 13W

Environmental:

Operating: 0°C to +40°C, stated
accuracy <70% RH

Storage:

-20°C to +60°C, <80% RH

1863 Voltage and Resistance Ranges

Voltage	Rmin (Full Scale)	Rmax	Useful Ranges
50VDC, 100VDC	50k Ω	2T Ω	7
200, 250, & 500VDC	500k Ω	20T Ω	7

1864 Voltage and Resistance Ranges

Voltage	Rmin (Full Scale)	Rmax	Useful Ranges
10VDC to 50VDC	50k Ω	2T Ω *	7*
50VDC to 100VDC	200k Ω	20T Ω	8
100VDC to 500VDC	500k Ω	20T Ω *	7*
500VDC to 1090VDC	5M Ω	200T Ω	8

*Recommended Limit.

Ordering Information

1863 and 1864 Megohmmeter, Portable

Description Catalog Number

1863 Megohmmeter 1863-9700

1864 Megohmmeter 1864-9700

Includes:

1863-0100

Instruction Manual

Calibration Certificate Traceable to NIST

Available Accessories:

630018

Lead Set

1863-11

Resistivity Test Fixture

